



DTM-7.4

Network Stereo Amplifier with HDMI

INTEGRA DTM-7.4 OVERVIEW

- 140W/ch x 2ch fully discrete amplifier
- 8K HDMI 4 in/1 out with ARC
- Chromecast built-in, AirPlay2, Roon ready
- 768kHz/32bit Premium D/A converter
- Custom-built components for Audio
- Dedicated Phono Circuit board with MM/MC cartridge type selector
- Full suite of custom integration software tools
- Works with Sonos for power and volume sync

HI-FI FOR ALL, BUILT FOR INTEGRATORS

Designed and engineered with meticulous attention to detail, the Integra DTM-7.4 Stereo Amplifier offers audiophile-grade sound alongside cutting-edge connectivity options and a full suite of custom installation features. This compact 2-channel amplifier seamlessly integrates into any home entertainment system, delivering high-resolution audio output while optimizing space efficiency.

Control4

CRESTRON
CERTIFIED INTEGRATED PARTNER

SAVANT

U-C

ELAN

RTI

domotz

OMC
PRO

JOSS

Works with
SONOS

Hi-Res
AUDIO

ROON
READY

WiFi
CERTIFIED

Bluetooth

Qualcomm®
aptX™ HD

HDMI 8K4K

TIDAL

pandora®

Spotify

amazon music

deezer

Chromecast
built-in

Works with
Apple AirPlay

Works with
Google Home



AUDIO	140W x 2ch (4Ω, 1% THD) 120W x 2ch (8Ω, 1% THD)
	Frequency response 5Hz - 100kHz (+1/-3dB Direct Mode)
	Speaker impedance: 4-16 ohms
	Tone control Bass(100Hz) & Treble (10KHz): +/- 10dB
	768KHz/32bits D/A converter - AK4452
INPUTS / OUTPUTS	Dedicated MM/MC Phono Circuit Board
	HDMI 4in / 1out – all supports 8K up to 40Gbps, and ARC
	Audio input: 3 Analog, 2 Optical, 1 Coaxial, Phono inputs, and Front/Rear USB
	Audio output : Main Stereo pre-out (x2) Subwoofer pre-out (x1) Zone2 Pre/lineout (x2)
	Wifi and Ethernet
	Gold plated premium speaker terminals
	RS232
NETWORK	Roon Ready certified
	Chromecast built-in for audio and AirPlay2
	Music services: Spotify, Amazon Music HD, Tidal, Deezer, Pandora and TuneIn radio
	Bluetooth receiver from mobiles and PC (SBC/AAC)
CONTROL AND SERVICE	Web setup, download configuration files via browser
	Front ping button (« Display » key) to see IP address
	IP control, RS232, IR in/out, and 12v triggers Control and remote diagnostic (C4, Creston, OvrC, Domotz)
	Compatible with OVRC Pro, Domotz, Luxul Pro Watch, VPN, and other monitoring platforms
	Onboard diagnostics tool kit, including test patterns and EDID/HDCEP adjustment, virtual remote; all available via web app
	Integra's most robust API ever, with discrete commands for virtually any AVR function
	Custom control drivers based on Integrator feedback. Developed and maintained by Integra's software team in Osaka, Japan
RACK KIT	Optional Rack-Mount Kit Available (IRK-155-3D)
DIMENSIONS	17 1/8" x 5 7/8" x 12 15/16" (435 x 149 x 328 mm)
WEIGHT	19.8lbs (9.0kg)
POWER CONSUMPTION	275W 35W at idle < 2W at standby
SKU	DTM7.4BMMM
EAN	4573211155709

Due to a policy of continuous product improvement, Integra reserves the right to change specifications and appearance without notice.